

Converter Box Series Hardware Specification	
Model	HD2SDI-S with Audio
Product Photo	HDMI to SDI UP/DOWN CONVERTER & AUDIO EMBEDDER SD 10 30 FOMER SOLOUT PC-188 7 8-184
Description	HDMI to SDI Up/Down Converter with Audio
Feature	 Built-in up/down conversion engine Auto source format detection (3G/HD/SD) High quality SDI Re-clock Engine (up to 3G-SDI) DIP switch for video mode and device configurations Mini-USB port for configurations and Firmware upgrade Multiple audio reception XLR x 1(a pair , XLR-L also for AES) Audio in x 1(a pair , Audio in-L also for SPDIF) HDMI embedded audio
Input	HDMI x 1 XLR x 1(a pair) Audio in x 1(a pair)
Output	Up/Down Converted SDI x 2
Supported Video Output Format	 Up/Down Converted SDI port ➤ 1080p60/50, 1080i60/50, 1080p30/25/24, 720p60/50 ➤ 1080p59.94, 1080i59.94, 720p59.94, 1080p29.97, 1080p23.98 ➤ 525i, 625i
Supported Audio Format	Up to 2 channels, 24bit, 48KHz
Plug & Play	✓
DC In	7.5V ~ 15V